

TET-EMTRON

TET-Emtron.
 80 STOCK Road. Phone:08 9296 3224
 HERNE HILL. 6056 Fax: 08 9296 3231
 Western Australia.
www.tet-emtron.com

HFTW

Tapped Whip for the Amateur Bands and 4WD Networks .

The new TET-Emtron HFTW tapped whip is designed to be used on a variety of different Amateur bands and most of the popular 4WD network and RFDS frequencies.

Amateur Bands.

The amateur bands covered are 80,60,40,30,20,17,15,12 and 10 metres. 6 metres can also be obtained with the use of a tuner.

4WD Networks.

You will see by the chart below that a lot of the frequencies are obtainable within the range of the amateur taps, and 8022 has its own tap. The others are obtainable by going as close as possible using the nearest frequency tap and the tip, and can usually be cleaned up with an internal tuner or coupler.

Asterisk* denotes tuner will most likely be required.

Amateur	RFDS	VMD	VKE-REIDS	VKS737
80m	4010*	3176*	3995*	3995*
60m	4030*	5127*	5135*	5455
40m	4055*	5270	5455	6796*
30m	5145*	7652*	11487*	8022
20m	5300	10158	11612*	10180
17m	5360	10203	14662*	11612*
15m	5410	13910*	14977*	14977*
12m	6890*	14865*		
10m	6920*	17463*		
6m*	6950*			



Features:

- Each half 810mm long.
- Computerized CNC wound.
- Large easy to read numbers.
- Strong 12.7mm pultruded fiberglass rod for longevity.
- Waterproof, glue lined Heatshrink to stop water ingress.
- O-ring sealed around Stainless tip.
- Joins in the middle for easy storage in your car boot.
- Comes in its own strong drawstring bag to keep your car clean.
- Wander lead is not soldered and can easily be repaired with a small screwdriver.

